



# FURTIF AMX5CK \_\_\_\_\_STAND-ALONE without safety module

# NON CONTACT CODED SWITCH WITH A LOCKING DEVICE

- → Automatic integrated self-monitoring
- → Electrical coded key locking : can be used in association with C4CK contactor
- → Detection distance/hysteresis/misalignment: 10 /+2 /±9 (mm)
- → 2NO 2A/48V + 2NC 24V/250mA
- > Yellow LED : decoding
- → Green LED: electrical interlocking
- → Mounting brackets, M12 connector integrated
- Polycarbonate housing
- → Temperature -20°C +60°C / Waterproof IP65


## SAFETY CATEGORY

AMX5CK: category 3\* according to EN954-1 category 4\*with a safety module


\* Regardless of number of switches in series



# WIRING DIAGRAM



#### **DIMENSIONS**



#### QUICK CONNECT PLUG

FRONT VIEW

AMX5CK



1 brown: 0v 5 grey: NO2 2 white: +24v 6 yellow: AUX1 3 blue: NO1 7 green: AUX2 4 pink: NO1 8 red: NO2

# AMX5CK in case of failure



Our switches are equipped with a 2A fuse in order to guarantee electrical protection.

### ADVICE

Transmission of key: contactor C4CKA and AMX5CK. It allows you to unlock a door of a dangerous zone; your safety is ensured by means of a locking device. It may replace an interlocking device.